




Guide on fixing May 15 bug

1. Using a PC connected to SMC7904WBRAS-N, change the date of this pc to any date before May 15th 2012.





2. Enter `http://192.168.2.1` and go to login page, then login with correct password.



3. Go to Management>Firmware Update, upgrade the firmware file.

The screenshot displays the SMC Networks Management web interface. The top navigation bar includes 'Setup', 'Advanced', 'Management' (circled in red), 'Status', and 'Help'. The left sidebar menu lists 'Management', 'System Management', 'Firmware Update' (circled in red), 'Access Controls', 'Diagnosis', 'Log Configuration', and 'Logout'. The main content area is titled 'FIRMWARE UPDATE' and contains the following instructions:

- Step 1:** Obtain an updated firmware image file from your ISP.
- Step 2:** Enter the path to the image file location in the box below or click the "Browse" button.
- Step 3:** Click the "Update Firmware" button once to upload the new image file.

A note states: "NOTE: The update process takes about 2 minutes to complete, and your DSL Router will reboot your router before the update is complete."

Below the instructions, the current firmware information is shown:

- Current Firmware Version:** SMC7904WBRAS-N v1.0.0.1
- Current Firmware Date:** 2010-12-17

The interface includes a 'Select File:' text input field, a 'Browse...' button (circled in red), and a 'Clear Config:' checkbox. At the bottom, there is an 'Update Firmware' button (circled in red).

4. Repeat step 1 to change the PC back to correct date after firmware upgrade.